
MultiModem[®] iCell

Intelligent Wireless Modem



User Guide

MultiModem® iCell User Guide
Intelligent Wireless Modem
MTCMR-E1, -C1, -G2, -H4, -EV2, optional -GP builds
S000484E, Revision E

Copyright

This publication may not be reproduced, in whole or in part, without prior expressed written permission from Multi-Tech Systems, Inc. All rights reserved.

Copyright © 2011 by Multi-Tech Systems, Inc.

Multi-Tech Systems, Inc. makes no representation or warranties with respect to the contents hereof and specifically disclaims any implied warranties of merchantability or fitness for any particular purpose.

Furthermore, Multi-Tech Systems, Inc. reserves the right to revise this publication and to make changes from time to time in the content hereof without obligation of Multi-Tech Systems, Inc., to notify any person or organization of such revisions or changes. Check Multi-Tech's Web site for current versions of our product documentation.

Revision History

<u>Revision</u>	<u>Date</u>	<u>Description</u>
A	05/17/10	Initial release of E1 build.
B	06/07/10	Release to add C1 build.
C	07/06/10	Release to add G2 build and –GP build options.
D	10/21/10	Release to add H4, EV2 builds and –GP build options.
E	07/29/11	Removed references to CD.

Trademarks and Logos

The Multi-Tech logo and *MultiModem* are registered trademarks of Multi-Tech Systems, Inc. Windows is a registered trademark of Microsoft in the U.S. and other countries. Other trademarks and trade names mentioned in this publication belong to their respective owners.

Contacting Multi-Tech Support

In order to better serve our customers, manage support requests and shorten resolution times, we have created the online web portal allowing you to submit questions regarding Multi-Tech products directly to our technical support team. Get answers to your most complex questions, ranging from implementation, troubleshooting, product configuration, firmware upgrades and much more.

To create an account and submit a Support Case on the Portal, visit: <https://support.multitech.com>

Online Web Portal

<https://support.multitech.com>

The Knowledge Base provides immediate answers to [your](#) questions and gives you access to support resolutions for all Multi-Tech products. Visit our support area on the website for other support services.

Knowledge Base and Support Services

www.multitech.com/support.go

World Headquarters

Multi-Tech Systems, Inc.
2205 Woodale Drive
Mounds View, Minnesota 55112
Phone: 763-785-3500 or 800-328-9717
Fax: 763-785-9874

Technical Support

Business Hours: M-F, 9am to 5pm CST

Country

Europe, Middle East, Africa:
U.S., Canada, all others:

By Email

support@multitech.co.uk
support@multitech.com

By Phone

+(44) 118 959 7774
(800) 972-2439 or (763) 717-5863

Warranty

To read the warranty statement for your product, please visit: <http://www.multitech.com/warranty.go>


Contents

Chapter 1 – Product Description and Specifications	5
Related Documentation	6
Universal IP	6
MultiModem MTCMR-E1 (EDGE).....	6
MultiModem MTCMR-C1 (CDMA)	6
MultiModem MTCMR-G2 (GPRS)	6
MultiModem MTCMR-H4 (HSPA)	6
MultiModem MTCMR-EV2 (EV-DO).....	6
Package Contents	7
Safety	7
General Safety.....	7
RF Interference Issues.....	7
Vehicle Safety.....	8
Maintenance of the Wireless MultiModem.....	8
Handling Precautions	8
Front Panel	9
LEDs.....	9
Back Panel	10
Specifications	11
Power	12
RF Specifications	13
Antenna Specifications	14
GSM/EGSM Antenna Requirements/Specifications	14
Antennas Available from Multi-Tech Systems, Inc.	14
PTCRB Requirements Note	14
FCC Requirements Note.....	14
Global Positioning System (GPS).....	15
GPIO (General Purpose Input/Output) Connector	15
GPIO DC Characteristics	16
RS232 9-Pin Functions of the Female End Connector	16
Chapter 2 – Activation and Installation	17
Activating Your Wireless Account	17
Phone Numbers for the Wireless Modem	17
Installing the SIM Card (if required)	17
Connecting the Antenna, Serial Cable, GPIO Cable, and Power	18
Connecting Direct DC Power (Optional)	19
Attaching the Modem to a Flat Surface	19

Installing the USB Virtual COM Port	20
Before You Begin.....	20
Installing the Modem Driver	21
Verifying that the Modem is Successfully Installed	25
Chapter 3 – Using Your Wireless Modem	26
Phone Numbers for the Wireless Modem	26
Examples of Useful AT Commands	26
HyperTerminal	26
AT Commands	26
Checking the Modem’s Identity.....	27
Connecting to the Internet	27
Connecting to a CDMA Network for Internet Access.....	27
Connecting to an EDGE/GPRS Network for Internet Access.....	27
Creating Dial-Up Connection in Windows Vista and XP.....	28
Generic Dial-Up Method - Non-Windows.....	29
Appendix A – Regulatory Compliance	31
EMC, Safety, and R&TTE Directive Compliance	31
International Modem Restrictions.....	31
FCC Part 15 Class B Statement	31
Industry Canada	31
Appendix B – DC Power Cable	32
Appendix C – Environmental Information	33
Waste Electrical and Electronic Equipment (WEEE) Statement.....	33
REACH Statement	33
Restriction of the Use of Hazardous Substances (RoHS)	34
C – RoHS.....	35
INDEX	36

Chapter 1 – Product Description and Specifications

The Multi-Tech MultiModem® iCell is a mid-range wireless modem containing an embedded TCP/IP protocol stack for Internet connectivity, serial and USB connectors for modem configuration, and a General Purpose Input/Output (GPIO) connector for customer interface connection. You can mount MultiModem iCells on a desktop or panel.



Model	Description
MTCMR-E1	Quad-band E-GPRS Class 12 performance
MTCMR-E1-GP	Quad-band E-GPRS Class 12 performance; GPS functionality
MTCMR-C1	Multi-band CDMA2000 1xRTT performance
MTCMR-C1-GP	Multi-band CDMA2000 1xRTT performance; GPS functionality
MTCMR-G2	Quad-band GSM/GPRS Class 10 performance
MTCMR-G2-GP	Quad-band GSM/GPRS Class 10 performance; GPS functionality
MTCMR-H4	Standards based tri-band UMTS/HSPA performance
MTCMR-H4-GP	Standards based tri-band UMTS/HSPA performance; GPS functionality
MTCMR-EV2	Dual-band 800/1900 MHz with receive diversity support on EVDO bands
MTCMR-EV2-GP	Dual-band 800/1900 MHz with receive diversity support on EVDO bands; GPS functionality

The MTCMR contains an embedded TCP/IP protocol stack to bring Internet connectivity to any device without making changes to its hardware design. Using the Internet protocols and the wireless connection to an IP network, the modem sends and receives data over the Internet. The modem offers short message service (SMS) features such as text and PDU, Point-to-point (MT/MO) and cell broadcast.

The MultiModem iCell modem delivers some of the fastest cellular wireless data speeds using the various Internet protocols. This is ideal for highly data-intensive applications such as remote video surveillance and other multimedia applications where you are sending digital images, web pages and photographs.

The MultiModem iCell modem is designed around a wide variety of interface options including serial RS-232, USB, and General Purpose Input/Output (GPIO). The serial RS-232 and USB connections provide seamless connectivity for configuration of your application. The GPIO interface provides five user-configurable GPIO's as CMOS input or output ports to be connected to a customer's peripheral device. A customer application in which the GPIO interface could be used is one with a monitoring device connected to the GPIO interface in which the monitoring device triggers an event in the IP stack to establish a TCP or UDP socket connection or send an email stating that the monitoring device was triggered by high water.

Related Documentation

Universal IP

All MultiModem iCell modems are equipped with an embedded TCP/IP protocol stack to automate the connection process and open a socket for bidirectional data transmission. Multi-Tech's Universal IP supports Telnet, SMTP/POP, FTP, TCP, UDP, PPP as well as other automatic call management options.

AT Commands: The embedded TCP/IP stack on the MultiModem iCell modems is configured using the Universal IP (UIP) AT Commands. These commands are documented in the Reference Guide document number S000457x.

MultiModem MTCMR-E1 (EDGE)

The MultiModem iCell MTCMR-E1 wireless modem delivers some of the fastest cellular wireless data speeds using EDGE technology. It allows users to connect to the Internet, send and receive data up to three times faster than possible with an ordinary GSM/GPRS network making it ideal for highly data-intensive multimedia applications.

AT Commands: The MultiModem MTCMR-E1 wireless modem is configured using the EDGE AT Commands. These commands are documented in the Reference Guide for the MultiModem Wireless EDGE Modems, document number S000474x.

MultiModem MTCMR-C1 (CDMA)

The MultiModem iCell MTCMR-C1 wireless modem offers standards-based multi-band CDMA2000 1xRTT performance. The ready-to-deploy, standalone modem allows developers to add wireless communication to products with a minimum of development time and expense.

AT Commands: The MultiModem MTCMR-C1 wireless modem is configured using the CDMA AT Commands. These commands are documented in the Reference Guide for the MultiModem Wireless CDMA Modems, document number S000478x.

MultiModem MTCMR-G2 (GPRS)

The MultiModem iCell MTCMR-G2 wireless modem offers standards-based quad-band GSM/GPRS Class 12 performance. Ready to deploy, standalone data modem allows developers to add wireless communication to products with a minimum of deployment time and expense.

AT Commands: The MultiModem MTCMR-G2 wireless modem is configured using the GPRS AT Commands. These commands are documented in the Reference Guide for the MultiModem Wireless GPRS Modems, document number S000463.

MultiModem MTCMR-H4 (HSPA)

The MultiModem iCell MTCMR-H4 delivers some of the fastest cellular data speeds by using HSPA technology. Based on industry-standard open interfaces, the SocketModem cellular modem is equipped with quad-band, high-speed RS232 technology, which means it can be used worldwide on all existing GSM networks.

AT Commands: The MultiModem MTCMR-H4 wireless modem is configured using the HSPA AT Commands. These commands are documented in the Reference Guide number S000483x.

MultiModem MTCMR-EV2 (EV-DO)

The MultiModem iCell MTCMR-EV2 wireless modems are 3G units supporting CDMA EV-DO Rev A and below. Based on industry-standard open interfaces, the MultiModem iCell is equipped with dual-band 800/1900 MHz bands with receive diversity support on both bands.

AT Commands: The MultiModem MTCMR-EV2 wireless modem is configured using the EV-DO AT Commands. These commands are documented in the Reference Guide number S000482x.

Package Contents

Note: Your wireless provider supplies the SIM card (not needed for -C1/ -EV2 versions).

Unbundled Package with No Accessories	Bundled Package with Accessories
1 modem Note: You must supply mounting screws, AC or DC power supply, and antenna(s).	1 modem 1 antenna (-GP builds have an additional GPS antenna) 1 RS232 cable 1 USB cable 1 GPIO cable 1 power supply (-GP builds do not include power supply) Note: You must supply mounting screws.

Safety

General Safety

The modem is designed for and intended to be used in fixed and mobile applications. “Fixed” means that the device is physically secured at one location and is not able to be easily moved to another location. “Mobile” means that the device is designed to be used in other than fixed locations.

Caution: Maintain a separation distance of at least 20 cm (8 inches) between the transmitter’s antenna and the body of the user or nearby persons. The Modem is not designed for or intended to be used in portable applications within 20 cm. (8 inches) of the body of the user.

RF Interference Issues

It is important to follow any special regulations regarding the use of radio equipment due in particular to the possibility of radio frequency, RF, interference. Please follow the safety advice given below carefully.

- Switch OFF your MultiModem when in an aircraft. The use of cellular telephones in an aircraft may endanger the operation of the aircraft, disrupt the cellular network and is illegal. Failure to observe this instruction may lead to suspension or denial of cellular telephone services to the offender, or legal action or both.
- Switch OFF your MultiModem when around gasoline or diesel-fuel pumps and before filling your vehicle with fuel.
- Switch OFF your MultiModem in hospitals and any other place where medical equipment may be in use.
- Respect restrictions on the use of radio equipment in fuel depots, chemical plants or where blasting operations are in progress.
- There may be a hazard associated with the operation of your MultiModem close to inadequately protected personal medical devices such as hearing aids and pacemakers. Consult the manufacturers of the medical device to determine if it is adequately protected.
- Operation of your MultiModem close to other electronic equipment may also cause interference if the equipment is inadequately protected. Observe any warning signs and manufacturers’ recommendations.

Vehicle Safety

- Do not use your MultiModem while driving.
- Respect national regulations on the use of cellular telephones in vehicles. Road safety always comes first.
- If incorrectly installed in a vehicle, the operation of MultiModem telephone could interfere with the correct functioning of vehicle electronics. To avoid such problems, be sure that qualified personnel have performed the installation. Verification of the protection of vehicle electronics should be part of the installation.
- The use of an alert device to operate a vehicle's lights or horn on public roads is not permitted.

Maintenance of the Wireless MultiModem

Your wireless MultiModem is the product of advanced engineering, design, and craftsmanship and should be treated with care. The suggestions below will help you to enjoy this product for many years.

- Do not expose the MultiModem to any extreme environment where the temperature or humidity is high.
- Do not attempt to disassemble the MultiModem. There are no user serviceable parts inside.
- Do not expose the MultiModem to water, rain, or spilled beverages. It is not waterproof.
- Do not abuse your MultiModem by dropping, knocking, or violently shaking it. Rough handling can damage it.
- Do not place the MultiModem alongside computer discs, credit or travel cards, or other magnetic media. The information contained on discs or cards may be affected by this device.
- The use of accessories not authorized by Multi-Tech or not compliant with Multi-Tech's accessory specifications may invalidate the warranty of the MultiModem.
- In the unlikely event of a fault in the MultiModem, contact Multi-Tech Technical Support.

Handling Precautions


All devices must be handled with certain precautions to avoid damage due to the accumulation of static charge. Although input protection circuitry has been incorporated into the devices to minimize the effect of this static build up, proper precautions should be taken to avoid exposure to electrostatic discharge during handling and mounting.

Front Panel

The front panel includes two groups of LEDs:

- The first LED group displays modem activity, such as transmit and receive data, carrier detection, link status, terminal ready indicating connection to the pc, and the power indicator.
- The three Signal LEDs display the signal strength level of the wireless connection.

For some models, a SIM door is included on the right side of the modem, providing access to the SIM card holder.




LEDs

LED Indicators			
TD	Transmit Data: Lit when modem is transmitting data. Not valid while in USB mode.		
RD	Receive Data: Lit when modem is receiving data. Not valid while in USB mode.		
CD	Carrier Detect: Lit when data connection has been established. Not valid while in USB mode.		
LS	Link Status LED is dependent on the model:		
	-E1 version* (When AT^SSYNC=1)	-G2 and -C1 versions	-H4 and -EV2 versions
	<p>Permanently off. ME is in one of the following modes: Power Down mode, Airplane mode Non-Cyclic Sleep mode with no temporary wake-up event in progress.</p> <p>600 ms on/600 ms off Limited Network Service: No SIM card inserted or no PIN entered, or network search in progress or ongoing user authentication, or network login in progress.</p> <p>75 ms on/3 sec off Idle mode: The mobile is registered to the GSM network (monitoring control channels and user interactions). No call is in progress.</p> <p>75 ms on/ 75 ms off/75 ms on/3 sec off One or more GPRS contexts activated.</p> <p>500 ms on/ 25 ms off Packet switched data transfer in progress.</p> <p>Permanently on CSD call – Connected to remote party.</p>	<p>Continuous “on” state indicates that the wireless modem is not registered on the network.</p> <p>Flashing states:</p> <p>200 ms on / 2 sec off Indicates registration on network.</p> <p>200 ms on / 600 ms off Indicates it is registered on a network and communication is in progress.</p> <p>Off state. Modem is off (not ready) or in download mode.</p>	<p>Continuous “on” state indicates that the modem is powered on, and registered on the network.</p> <p>Slow flashing state (5 seconds) indicates the modem powered on and searching for registration on a network.</p> <p>Fast flashing state (0.3 seconds) indicates the modem is transmitting or receiving.</p> <p>Off state. Modem is off (not powered).</p>
	TR	Terminal Ready: Commonly referred to as “Data Terminal Ready”, this is a readiness signal from the PC.	
PWR / GPS	<p>Power: Indicates presence of DC power when lit.</p> <p>GPS: If a valid GPS signal has been received, the PWR/GPS LED will blink at 1 second ON, and 0.5 second OFF. If GPS signal is invalid, the PWR/GPS LED will be on solid.</p>		
Signal	<p>ALL OFF – Unit is off, not registered on a network or has an extremely weak signal ($0 \leq \text{RSSI} < 6$).</p> <p>1 Bar ON – Very weak signal ($7 \leq \text{RSSI} < 14$)</p> <p>1 and 2 Bars ON – Weak signal ($15 \leq \text{RSSI} < 23$)</p> <p>1, 2, and 3 Bars ON – Good signal ($24 \leq \text{RSSI} < 31$)</p>		

*To be accurate, the AT^SSYNC command must be set to 1 so that factory default LED timings are used.

Back Panel

The modem's back panel differs only if you purchased the GP model which includes a connector for a GPS antenna. The GPS antenna connector is located between the power connector and the RS-232 connector. The far right connector is for the wireless antenna.



Specifications

Features	MTCMR-E1	MTCMR-C1	MTCMR-G2	MTCMR-H4	MTCMR-EV2
Performance	EDGE: E-GPRS Class 12, GPRS: Class 10	CDMA2000 1xRTT	GPRS Class 10	HSPA	CDMA2000 1xRTT EV-DO Rev. A
Band, Frequency	Quad-band GSM/GPRS/EDGE 850/900/1800/1900 MHz	Dual-band 800/1900 MHz CDMA; 800 MHz and 800/1900 MHz with R-UIM support	Quad-band GSM 850/900/1800/1900 MHz	HSUPA / HSDPA / UMTS Triple-band: 2100/1900/850 MHz with Rx diversity	Dual-band 800/1900 MHz CDMA; 800 MHz and 800/1900 MHz with R-UIM support
Packet Data	EDGE: E-GPRS Up to 240K bps, coding scheme MCS 1-9, mobile station Class B, LLC layer, 4 time slots. GPRS: Full PBCCH support, coding scheme 1-4, mobile station Class B	Up to 153.6K bps forward and reverse	Up to 85.6K bps, coding schemes CS1 to CS4	HSDPA data service of up to 7.2 Mbps HSUPA data service of up to 5.76 Mbps	Up to 153.6K bps forward and reverse
Circuit-Switched Data	Up to 14.4K bps, non-transparent	IS-95A, IS-95B up to 14.4K bps forward and reverse	Up to 14.4K bps transparent and non-transparent	Up to 14.4K bps transparent and non- transparent	IS-95A, IS-95B up to 14.4K bps forward and reverse
Short Message Services-SMS	Text & PDU, Point-to-Point (MO/MT), cell broadcast	Text & PDU, Point-to-Point (MO/MT), cell broadcast	Text & PDU, Point-to-Point, cell broadcast	Text & PDU, Point-to-Point (MO/MT), cell broadcast	Text & PDU, Point-to-Point (MO/MT), cell broadcast
Antenna Connector	RF Antenna: 50 ohm SMA (female connector)	RF Antenna: 50 ohm SMA (female connector)	RF Antenna: 50 ohm SMA (female connector)	RF Antenna: 50 ohm SMA (female connector)	RF Antenna: 50 ohm SMA (female connector)
SIM Connector	Standard 1.8 and 3V SIM slot	-	Standard 1.8 and 3V SIM slot	Standard 1.8 and 3V SIM slot	-
External Connectors	RS2323: DE9; GPIO: 6 pin 2x3 style; Power: 2.5mm miniature (screw-on); USB: Type B				
Voltage	9V to 32 VDC	9V to 32 VDC	9V to 32 VDC	9V to 32 VDC	9V to 32 VDC
Physical Description	4.9" Width x 1.1" Height x 3.1" Depth 8 ounces 12.4 cm Width x 2.8 cm Height x 7.9 cm Depth 227 grams				
Operating Temperature *	-35° to +75° C UL listed @ 40°	-40° to +85° C UL listed @ 40°	-40° to +85° C UL listed @ 40°	-30° to +60° C UL listed @ 40°	-30° to +85° C UL listed @ 40°
Storage Temp	-40° to +85° C	-40° to +85° C	-40° to +85° C	-40° to +85° C	-40° to +85° C
Humidity	Relative humidity 20% to 90% noncondensing				
Certifications	EMC Compliance FCC Part 15 Class B EN55022 Class B Radio Compliance FCC Part 22, 24 RSS132,133 EN301 489-1 EN301 489-3 (-GP only) EN301 489-7 EN301 511 EN301 908 AS/ACIF S042.1, S042.3 Safety: UL60950-1 cUL60950-1 IEC60950-1 Network: PTCRB	EMC Compliance FCC Part 15 Class B EN55022 Class B Radio Compliance FCC Part 22, 24 RSS132,133 Safety: UL60950-1 cUL60950-1 IEC60950-1 Network: CDG 1&2	EMC Compliance FCC Part 15 Class B EN55022 Class B Radio Compliance FCC Part 22, 24 RSS132,133 EN301 489-1 EN301 489-3 (-GP only) EN301 489-7 EN301 511 EN301 908 AS/ACIF S042.1, S042.3 Safety: UL60950-1 cUL60950-1 IEC60950-1 Network: PTCRB	EMC Compliance FCC Part 15 Class B EN55022 Class B Radio Compliance FCC Part 22, 24 RSS132,133 EN301 489-1 EN301 489-3 (-GP only) EN301 489-7 EN301 489-24 EN301 511 EN301 908 AS/ACIF S042.1, S042.3 Safety: UL60950-1 cUL60950-1 IEC60950-1 Network: PTCRB	EMC Compliance FCC Part 15 Class B EN55022 Class B Radio Compliance FCC Part 22, 24 Safety: UL60950-1 cUL60950-1 IEC60950-1 Network: CDG 1&2

* UL Listed @ 40° C, limited by power supply. UL Certification does not apply or extend to an ambient above 40° C and has not been evaluated by UL for ambient greater than 40° C.

“UL has evaluated this device for use in ordinary locations only. Installation in a vehicle or other outdoor locations has not been evaluated by UL. UL Certification does not apply or extend to use in vehicles or outdoor applications or in ambient above 40° C.”

Power

MTCMR-E1	MTCMR-C1	MTCMR-G2	MTCMR-H4	MTCMR-EV2
<p>Sleep .091A, .84W @ 9V, .048A, .96W @ 20V, .034A, 1.088W @ 32V</p> <p>Typical .149A, 1.37W @ 9V, .077A, 1.54W @ 20V, .054A, 1.73W @ 32V</p> <p>Max .416A, 3.77W @ 9V, .190A, 3.80W @ 20V, .124A, 3.97W @ 32V</p> <p>Peak 2.5A @ 9V, 0.895A @ 20V, 0.625A @ 32V</p>	<p>Sleep .048A, .44W @ 9V, .027A, .54W @ 20V, .021A, .67W @ 32V</p> <p>Typical .128A, 1.18W @ 9V, .065A, 1.30W @ 20V, .046A, 1.47W @ 32V</p> <p>Max .360A, 3.31W @ 9V, .171A, 3.42W @ 20V, .115A, 3.68W @ 32V</p>	<p>Sleep .069A, .64W @ 9V, .038A, .76W @ 20V, .030A, .96W @ 32V</p> <p>Typical .109A, 1.01W @ 9V, .056A, 1.12W @ 20V, .041A, 1.3W @ 32V</p> <p>Max .194A, 1.79W @ 9V, .096A, 1.92W @ 20V, .065A, 2.1W @ 32V</p> <p>Peak 1.53A @ 9V, 0.668A @ 20V, 0.453A @ 32V</p>	<p>GSM 850</p> <p>Sleep 0.090A, 0.83W @ 9V, 0.050A, 1.00W @ 20V, 0.035A, 1.12W @ 32V</p> <p>Typical 0.150A, 1.39W @ 9V, 0.076A, 1.52W @ 20V, 0.051A, 1.63W @ 32V</p> <p>Max 0.405A, 3.73W @ 9V, 0.186A, 3.72W @ 20V, 0.120A, 3.84W @ 32V</p> <p>Peak 2.25A @ 9V, 0.90A @ 20V, 0.63A @ 32V</p> <p>HSPA</p> <p>Sleep 0.090A, 0.83W @ 9V, 0.050A, 1.00W @ 20V, 0.035A, 1.12W @ 32V</p> <p>Typical 0.330A, 3.04W @ 9V, 0.165A, 3.30W @ 20V, 0.105A, 3.36W @ 32V</p> <p>Max 0.570A, 5.23W @ 9V, 0.266A, 5.32W @ 20V, 0.170A, 5.44W @ 32V</p>	<p>CDMA2000</p> <p>Sleep 0.061A, 0.56W @ 9V, 0.030A, 0.60W @ 20V, 0.023A, 0.74W @ 32V</p> <p>Typical 0.160A, 1.47W @ 9V, 0.081A, 1.62W @ 20V, 0.055A, 1.76W @ 32V</p> <p>Max 0.485A, 4.41W @ 9V, 0.230A, 4.60W @ 20V, 0.152A, 4.86W @ 32V</p> <p>EV-DO</p> <p>Sleep 0.108A, 1.00W @ 9V, 0.052A, 1.04W @ 20V, 0.041A, 1.31W @ 32V</p> <p>Typical 0.330A, 3.04W @ 9V, 0.165A, 3.30W @ 20V, 0.105A, 3.36W @ 32V</p> <p>Max 0.580A, 5.27W @ 9V, 0.313A, 6.26W @ 20V, 0.205A, 6.56W @ 32V</p>
<p>MTCMR-E1-GP</p> <p>Sleep .098A, .91W @ 9V, .051A, 1.02W @ 20V, .035A, 1.125W @ 32V</p> <p>Typical .160A, 1.48W @ 9V, .080A, 1.60W @ 20V, .056A, 1.79W @ 32V</p> <p>Max .410A, 3.77W @ 9V, .190A, 3.80W @ 20V, .122A, 3.90W @ 32V</p> <p>Peak 2.25A @ 9V, 0.890A @ 20V, 0.609A @ 32V</p>	<p>MTCMR-C1-GP</p> <p>Sleep .096A, .89W @ 9V, .052A, 1.04W @ 20V, .037A, 1.18 W @ 32V</p> <p>Typical .175A, 1.62W @ 9V, .092A, 1.84W @ 20V, .062A, 1.98W @ 32V</p> <p>Max .435A, 4.00W @ 9V, .205A, 4.10W @ 20V, .135A, 4.32W @ 32V</p>	<p>MTCMR-G2-GP</p> <p>Sleep .083A, .77W @ 9V, .046A, .92W @ 20V, .036A, 1.15W @ 32V</p> <p>Typical .130A, 1.19W @ 9V, .067A, 1.34W @ 20V; .050A, 1.6W @ 32V</p> <p>Max .233A, 2.13W @ 9V, .115A, 2.30W @ 20V, .078A, 2.5W @ 32V</p> <p>Peak 1.83A @ 9V, 0.801A @ 20V, 0.543A @ 32V</p>	<p>MTCMR-H4-GP</p> <p>GSM 850</p> <p>Sleep 0.090A, 0.83W @ 9V, 0.050A, 1.00W @ 20V, 0.035A, 1.12W @ 32V</p> <p>Typical 0.167A, 1.54W @ 9V, 0.080A, 1.60W @ 20V, 0.055A, 1.76W @ 32V</p> <p>Max 0.435A, 3.97W @ 9V, 0.195A, 3.90W @ 20V, 0.127A, 4.06W @ 32V</p> <p>Peak 2.60A @ 9V, 0.91A @ 20V, 0.60A @ 32V</p> <p>HSPA</p> <p>Sleep 0.090A, 0.83W @ 9V, 0.050A, 1.00W @ 20V, 0.035A, 1.12W @ 32V</p> <p>Typical 0.351A, 3.24W @ 9V, 0.172A, 3.44W @ 20V, 0.115A, 3.68W @ 32V</p> <p>Max 0.586A, 5.38W @ 9V, 0.280A, 5.60W @ 20V, 0.180A, 5.76W @ 32V</p>	<p>MTCMR-EV2-GP</p> <p>CDMA2000</p> <p>Sleep 0.119A, 1.10W @ 9V, 0.062A, 1.24W @ 20V, 0.044A, 1.41W @ 32V</p> <p>Typical 0.220A, 2.02W @ 9V, 0.110A, 2.20W @ 20V, 0.075A, 2.40W @ 32V</p> <p>Max 0.560A, 5.09W @ 9V, 0.265A, 5.30W @ 20V, 0.175A, 5.60W @ 32V</p> <p>EV-DO</p> <p>Sleep 0.167A, 1.54W @ 9V, 0.087A, 1.74W @ 20V, 0.062A, 1.98W @ 32V</p> <p>Typical 0.370A, 3.40W @ 9V, 0.192A, 3.84W @ 20V, 0.121A, 3.87W @ 32V</p> <p>Max 0.625A, 5.68W @ 9V, 0.345A, 6.90W @ 20V, 0.225A, 7.20W @ 32V</p>

NOTE: Multi-Tech Systems, Inc. recommends that the customer incorporate a 10% buffer into their power source when determining product load.

RF Specifications

	GSM 850	EGSM 900	GSM 1800	GSM 1900	CDMA 800	CDMA 1900
Frequency RX	869 to 894 MHz	925 to 960 MHz	1805 to 1800 MHz	1930 to 1990 MHz	869 to 894 MHz	1930 to 1990 MHz
Frequency TX	824 to 849 MHz	880 to 915 MHz	1710 to 1785 MHz	1850 to 1910 MHz	824 to 849 MHz	1850 to 1910 MHz
RF Power Stand	2W at 12.5% duty cycle	2W at 12.5% duty cycle	1W at 12.5% duty cycle	1W at 12.5% duty cycle	-	-

Antenna Specifications

GSM/EGSM Antenna Requirements/Specifications

Frequency Range:	824 – 960 MHz / 1710 – 1990 MHz
Impedance:	50 Ohms
VSWR:	<2.0:1
Typical Radiated Gain:	3 dBi on azimuth plane
Radiation:	Omni
Polarization:	Vertical
Wave:	Half Wave Dipole

Antennas Available from Multi-Tech Systems, Inc.

Quad Band Description

	Qty	Part Number
Hinged Right Angle 800/900/1800/1900 MHz Cellular Modem Antenna	1	ANQB-1HRA
Hinged Right Angle 800/900/1800/1900 MHz Cellular Modem Antenna	10	ANQB-10HRA
Hinged Right Angle 800/900/1800/1900 MHz Cellular Modem Antenna	50	ANQB-50HRA

Dual Band Description

	Qty	Part Number
Hinged Right Angle 900/1800 MHz Cellular Modem Antenna	1	ANF1-1HRA
Hinged Right Angle 900/1800 MHz Cellular Modem Antenna	10	ANF1-10HRA
Hinged Right Angle 900/1800 MHz Cellular Modem Antenna	50	ANF1-50HRA
Hinged Right Angle 800/1900 MHz Cellular Modem Antenna	1	ANCF2-1HRA
Hinged Right Angle 800/1900 MHz Cellular Modem Antenna	10	ANCF2-10HRA
Hinged Right Angle 800/1900 MHz Cellular Modem Antenna	50	ANCF2-501HRA

Mag Mount Dual Band Description

	Qty	Part Number
Mag Mount 900/1800 MHz 1/2 Wave Cellular Antenna, 12.5"	1	ANF1-1MMHW
Mag Mount 900/1800 MHz 1/2 Wave Cellular Antenna, 12.5"	10	ANF1-10MMHW
Mag Mount 900/1800 MHz 1/2 Wave Cellular Antenna, 12.5"	50	ANF1-50MMHW
Mag Mount 900/1800 MHz 1/4 Wave Cellular Antenna, 4"	1	ANF1-1MMQW
Mag Mount 900/1800 MHz 1/4 Wave Cellular Antenna, 4"	10	ANF1-10MMQW
Mag Mount 900/1800 MHz 1/4 Wave Cellular Antenna, 4"	50	ANF1-50MMQW
Mag Mount 850/1900 MHz 1/2 Wave Cellular Antenna, 12.5"	1	ANCF2-1MMHW
Mag Mount 850/1900 MHz 1/2 Wave Cellular Antenna, 12.5"	10	ANCF2-10MMHW
Mag Mount 850/1900 MHz 1/2 Wave Cellular Antenna, 12.5"	50	ANCF2-50MMHW
Mag Mount 850/1900 MHz 1/4 Wave Cellular Antenna, 4"	1	ANCF2-1MMQW
Mag Mount 850/1900 MHz 1/4 Wave Cellular Antenna, 4"	10	ANCF2-10MMQW
Mag Mount 850/1900 MHz 1/4 Wave Cellular Antenna, 4"	50	ANCF2-50MMQW

GPS Description

	Qty	Part Number
Mag Mount GPS Antenna, 5 Meter Cable	1	ANGPS-1MM
Mag Mount GPS Antenna, 5 Meter Cable	10	ANGPS-10MM

PTCRB Requirements Note

There cannot be any alteration to the authorized antenna system. The antenna system must be the same type with similar in-band and out-of-band radiation patterns and maintain the same specifications.

FCC Requirements Note

The antenna gain, including cable loss, for the radio you are incorporating into your product design must not exceed the requirements at 850 MHz and 1900 MHz as specified by the FCC grant for mobile operations and fixed mounted operations as defined in 2.1091 and 1.1307 of the FCC rules for satisfying RF exposure compliance. The antenna used for transmitting must be installed to provide a separation distance of at least 20 cm from all persons and must not transmit simultaneously with any other antenna transmitters. User and installers must be provided with antenna installation instructions and transmitter operating conditions to satisfying RF exposure compliance.

Global Positioning System (GPS)

Technical Specifications

Receiver Type	L1 Frequency, GPS C/A code, SBAS Capable, 51 Channel Acquisitions, 14 Channel Tracking
Accuracy	Position 2.5m CEP, Velocity 0.1m/sec
Open Sky TTFF	Hot start 1 second, Cold start 29 seconds average, Reacquisition <1s
Sensitivity Tracking	-161dBm
Update Rate	1 Hz standard
Dynamics	4G
Operational Limits	Altitude <18,000m or Velocity < 515m/s
Datum	Default WGS-84
Interface	UART
Protocol	NMEA-0183 V3.01, GGA, GLL, GSA, GSV, RMC, VTG

Global Positioning System (GPS) – Underwriters Laboratories, Inc. Statement

Underwriters Laboratories Inc. (“UL”) has not tested the performance or reliability of the Global Positioning System (“GPS”) hardware, operating software or other aspects of this product. UL has only tested for fire, shock or casualties as outlined in UL’s Standard(s) for Safety. UL60950-1 Certification does not cover the performance or reliability of the GPS hardware and GPS operating software. UL MAKES NO REPRESENTATIONS, WARRANTIES OR CERTIFICATIONS WHATSOEVER REGARDING THE PERFORMANCE OR RELIABILITY OF ANY GPS RELATED FUNCTIONS OF THIS PRODUCT.

GPIO (General Purpose Input/Output) Connector

You can configure the GPIO pins by using Universal IP (UIP) AT Commands. Refer to the Universal IP (UIP) AT Command Reference Guide that you can find on the Multi-Tech website. The following table explains the pins.

Pin Number	Description
Pin 1	DIO 0
Pin 2	DIO 1
Pin 3	DIO 2 / ADC 0
Pin 4	DIO 3 / ADC 1
Pin 5	ADC 2
Pin 6	Gnd

GPIO 6-Pin Connector

You can configure the GPIO pins independent of each other.

- Pin 1 Digital Input, 24 Volt tolerant.
- Pin 2 Digital Input, 24 Volt tolerant.
- You can configure Pin 3 as either Digital Input (5V tolerant TTL/CMOS levels) or Digital Output (3.3V High) or as an ADC input (0 to 3.3V rail)
- You can configure Pin 4 as either Digital Input (5V tolerant TTL/CMOS levels) or Digital Output (3.3V High) or as an ADC input (0 to 3.3V rail)
- Pin 5 is configured as an ADC input (0 to 3.3V rail)
- Pin 6 is GND and must be connected to the ground of the attached device

GPIO DC Characteristics

Pins 1, 2, Input Voltage

Parameter	Min	Max	Units
Input Low-level Voltage	0.3	1.0	V
Input High-level Voltage	3.0	24	V

Pins 3, 4, Input Voltage

Parameter	Min	Max	Units
Input Low-level Voltage	-0.3	0.8	V
Input High-level Voltage	2.0	5.5	V

Pins 3, 4, Output Voltage

Parameter	Min	Max	Units
Output Low-level Voltage	0.0	0.4	V
Output High-level Voltage	2.9	3.3	V

Pins 3, 4, Output Current

Parameter	Min	Max	Units
Output Current		2	mA


Pins 1, 2 are digital input only.

Pin 5 is an analog input only.

Pins 1-5 contain ESD protection.

RS232 9-Pin Functions of the Female End Connector

External Power	
Signal	IN/OUT
Pin 1 CD	O
Pin 2 RX	O
Pin 3 TX	I
Pin 4 DTR	I
Pin 5 GND	--
Pin 6 DSR	O
Pin 7 RTS	I
Pin 8 CTS	O
Pin 9 RI	O



Chapter 2 – Activation and Installation

Activating Your Wireless Account

To activate your wireless account, refer to the wireless account Activation Notices included with your unit. Follow the directions on the notice for your wireless network provider.

Phone Numbers for the Wireless Modem

Every wireless modem has a unique phone number. The phone number may simply be given to you by your wireless service provider or it may be on the SIM card or both. Wireless provider implementations may vary.

Installing the SIM Card (if required)

So that the modem can operate, it requires that you connect the power supply.

If you are operating on a GSM network, the modem also requires a SIM card (Subscriber Identity Module). To install the SIM:

1. Using a small Phillips screwdriver, remove the two SIM door screws and remove the SIM door.

Note: When changing a SIM, ensure that power is removed from the unit.



2. Insert the SIM card into the card holder. The illustration shows the correct SIM card orientation.
3. Verify that the SIM card fits into the holder properly and then replace the cover.


Connecting the Antenna, Serial Cable, GPIO Cable, and Power



1. Connect a suitable antenna to the SMA connector. For more information, see antenna specifications in Chapter 1.
2. If you are connecting to a serial interface, connect the DE9 connector (9-pin) of the RS232 cable to the RS232 connector on the modem and connect the other end to serial port on your PC.

If you are connecting to an USB interface, connect an USB cable to the USB connector on the back of the unit and the other end to the USB port on your PC.

3. Connect the GPIO cable to the I/O connector on the modem and the other end to the external device that the modem is monitoring.
4. Depending on the power source, connect either the power supply module with the appropriate blade or the optional DC power cable. If you are using the power supply module, remove the protective shipping cover. Attach the appropriate interchangeable blade piece to the power supply module.



Screw-on the power lead from the power supply module to the power connection on the modem. Now, plug the power supply into your power source.

Connecting Direct DC Power (Optional)

To connect the optional direct DC power:

1. Screw-on the DC power cable to the power connector on the modem.
2. Attach the two wires at the other end of the DC power cable to a DC fuse/terminal block on the vehicle where you are mounting the MultiModem.
3. Connect red wire to the "+" (positive) terminal and black wire to the "-" (negative) terminal. Be sure the GND connection is correct.

Warning: The device has over-voltage protection. To ensure complete protection, you can add additional filtering to the DC input.


Note: For automotive application: according to the type of application, you can use permanent "+" or key-switched "+" source. Connect the power supply to its source; for example, in a mobile situation, to the vehicle's DC fuse/terminal block.

Attaching the Modem to a Flat Surface

Before you mount your modem to a permanent surface, verify signal strength. For more information refer to Using Your Wireless Modem, Verify Signal Strength in Chapter 3.

Note: No matter which orientation you use to mount your MultiModem, ensure that the antenna is always vertical and pointing upward as the floor or ground may impede the antenna's performance.

You can mount the modem to a panel using screws spaced according to the measurement shown.



Installing the USB Virtual COM Port

This section describes how to install the virtual COM port. After you install the port, install the correct modem driver to the COM port.

Before You Begin

Before you install the port and driver, note the following:

- Download the user guides and the driver installation file from the Multi-Tech website. Store these files in a location where you can access them during installation.
- Windows XP, VISTA, 2003 Server, 2008 Server, Windows 7 (32-bit or 64-bit), Linux (Kernel 2.6.xx using CDC-ACM module) are supported.

Note: Some versions of Windows have an issue with the CDC-ACM driver (Usbser.sys). If you experience connection problems—such as problems with file downloads and web pages not loading—update the version of Usbser.sys. Microsoft article 925681 documents this fixable issue.

- For Linux, a 2.6 kernel is required. You can use the standard CDC-ACM driver.
- After installing the virtual com port, you can install the correct modem driver to the com port. Before you install the modem driver, ensure the USB port of the MTCMR is connected with a SIM card

To install the USB virtual COM port:

1. Ensure the SIM card (if applicable) is installed, then power on the MTCMR
2. Ensure that the USB cable is connected to your computer.
3. If you have not already done so, unzip the installation file that you downloaded from the Multi-Tech website.
4. From the area where you extracted the zip file, open the Drivers folder.
5. Run install.bat.
6. To start the driver pre-installation, click **Next**.




7. If the Windows Logo Testing panel appears, click **Continue Anyway**.
8. The process completes. Click **Finish**.




9. Install the modem driver, as described in the following section.

Installing the Modem Driver


1. From the Windows **Start** button, select **Control Panel**.
2. The Control Panel opens. Double-click **Phone and Modem Options**.




3. Click the **Modems** tab, then click **Add**.




4. On the Install New Modem panel, check **Don't detect my modem, I will select it from a list**. Then click **Next**.




5. On the Install New Modem panel, click **Have Disk**.




6. Browse to the location where you downloaded the driver file. Click **Next**.




7. Select the MTSMCIP_MTCMRIP.INF file.



8. Click **OK**.
9. In the Models group, scroll and select the model that is applicable to your modem.




10. Click **Next**.
11. Select the com port to which the MultiModem is connected.



If you know exactly which port your modem is on, click on that port; otherwise, check your Control Panel – Device Manager to see what COM port(s) is available. Click **Next**.

12. To finish the install, click **Finish**. You have now successfully installed the MultiModem driver to your PC.



Verifying that the Modem is Successfully Installed

After you have successfully installed the MultiModem driver, you return to the Phone and Modems Options screen. Make sure that the modem is now listed under the columns **Modem** and **Attached To** (the correct com port).

To verify that the installation is working:

1. Highlight the modem and then click **Properties**.
2. A Properties panel opens for the Multi-Tech modem. Click the **Diagnostics** tab, then click **Query Modem**.

Windows queries the Multi-Tech modem. If this process passes, the second box on this screen shows the columns **Command** and **Response**.

Note: To make sure that the modem is correctly being queried, look at the LED lights of the modem after you click **Query Modem**. The TR light illuminates. The TD and RD lights flicker.

3. If this process passes, then the modem is properly installed and ready for use. Click **OK** to close the modem Properties window. Then click **OK** to close the Phone and Modem Options window.

Chapter 3 – Using Your Wireless Modem

Phone Numbers for the Wireless Modem

- Every wireless modem has a unique phone number.
- Your wireless service provider may give you the phone number. The number may be on the SIM card. Wireless provider implementations may vary.

Examples of Useful AT Commands

HyperTerminal

To verify signal strength and roaming status, use a terminal application such as HyperTerminal. To open this program in Windows Vista or XP, go to **Start > All Programs > Accessories > Communications > HyperTerminal**. Other Windows operating systems have similar paths to HyperTerminal. If you cannot find HyperTerminal, use your system's online Help file.

AT Commands

You can use AT commands to operate, configure, and query your modem. AT commands for the MultiModem iCells are published in separate Reference Guides. You can find these guides on the Multi-Tech web site.

The following two commands let you query signal strength and roaming status.

Verifying Signal Strength

1. Using HyperTerminal, type **AT+CSQ**
2. The modem responds with the received signal strength (rssi).
3. The modem responds with the received signal strength (rssi) and the channel bit error rate (ber).

RSSI ranges from 0 to 31.

Signal Strength Verification – RSSI		
AT+CSQ xx Values	Signal Strength	LED Bars
0 - 10	Weak or Insufficient	1 Bar LED is lit
11 - 20	Average	1 Bar and 2 Bar LEDs are lit
21 – 31	Exceptional	1 Bar, 2 Bar, 3 Bar LEDs are lit
99	No signal	No light

BER ranges from 0 to 7 (Seven is the highest error rate).

Checking Network Registration and Roaming Status

To verify that the MultiModem is registered on the wireless network:

1. Open **HyperTerminal**, and type **AT+CREG?** for most models.

The modem responds to **AT+CREG?** in one of the following ways:

Network Registration Verification	
Value	Network Registration Status
0,0	The modem is not registered on any network
0,1	The modem is registered on the home network
0,5	The modem is registered on a network and it is roaming

2. If the modem indicates that it is not registered, verify the signal strength to determine if the problem is the strength of the received signal.

To verify the MTCMR-EV2:

1. Open a terminal program and send the command **AT!STATUS**
2. Several lines of information are returned. The second from the final response is either '**Modem has registered**' or '**Modem has NOT registered**'.

Checking the Modem's Identity

Use the **ATI** command (Note: This command is illustrated using the capital letter I after **AT**)

- Type **ATIO** (Note: The command ends in a zero)
- The manufacturing data displays.

Connecting to the Internet

You can setup Internet access using Windows Dial-Up Networking (DUN) on the computer that the MultiModem iCell is serving. For a GPRS network, you must create an Access Point Name in the Phone and Modem Options dialog in Windows Control Panel and then create your Windows DUN.

Connecting to a CDMA Network for Internet Access

Once you have activated your wireless account, you can establish your Internet connection through a Windows dial-up session. Setup procedures vary according to the type of wireless service provider used.

Requirements

- One MultiModem iCell modem
- The modem must be getting a proper signal and be showing a network registration through the wireless provider's network
- A PC running Windows XP or 2003 with the Multi-Tech drivers installed for your particular model

The following instructions are for Windows XP SP2 and Windows 2003. Every PC may have slight differences which may cause the instructions to be different. Use these instructions as a guide to help you understand what is required to set up an Internet connection through your wireless service provider for all operating systems.

Connecting to an EDGE/GPRS Network for Internet Access

After you insert the SIM card and complete all setup steps, you can establish an Internet connection through a Windows dial-up session.

Before You Begin

Before you begin, make sure:

- You have one MultiModem iCell modem, with an active SIM card
- The modem receives a proper signal and shows a network registration through the wireless provider's network
- Your PC is running Windows Vista or XP, with the Multi-Tech drivers installed

The following instructions are for Windows Vista and XP. Every PC may have slight differences which may cause the instructions to be different. Use these instructions as a guide to help you understand what is required to set up an Internet connection through your wireless service provider for all operating systems.

Setting up the Access Point Name (APN) into the Modem's Properties on your PC

For some models to connect to your provider's network, you must tell the modem the APN to which it connects. The APN is a server name that your account is setup on with your provider. Your provider gives you the APN.

1. Click **Start** then **Control Panel**.
2. In Control Panel, double-click **Phone and Modem Options**.
3. In the **Phone and Modem Options** screen, click the **Modems** tab. Highlight your MultiModem listed in the table and then click **Properties**.
4. A **Properties** window for your modem displays. For Windows Vista and later operating systems, click **Change Settings**.
5. Click the **Advanced** tab. In the **Extra Settings** group, in the **Extra initialization** text box, enter:
AT+CGDCONT=1,"IP", "<APN>"
For <APN>, enter in the correct APN for your account.
For example: **AT+CGDCONT=1"IP", "ISP.AT&T"**
6. Click **OK** to close the Properties window. Then click **OK** to close the Phone and Modems Options window.

Creating Dial-Up Connection in Windows Vista and XP

1. Select **Start** and then **Control Panel**.
2. In the Control Panel, double-click **Network Connections**.
3. On the Network Connections screen on the left-hand side under **Network Tasks**, click **Create a new connection**.
4. The New Connection Wizard appears. The wizard steps you through Internet connection setup. Click **Next**.
5. On the Network Connection Type screen, select **Connect to the Internet**, and then click **Next**.
6. On the Getting Ready screen, select **Set up my connection manually**, and then click **Next**.
7. On the Internet Connection screen, select **Connect using a dial-up modem**, and then click **Next**.
Note: After clicking on Next, you may or may not be asked to select which modem to use. If you have more than one modem installed in your PC, you must select the proper modem to use. If asked, select the Multi-Tech wireless modem that you installed.
8. On the Connection Name screen in the **ISP Name** box, type in a name for your new connection. You can give it any name that you would like. After you have typed in a name, click **Next**.
9. On the Phone Number to Dial screen, type in the number that specifies to the modem to connect to your provider's Internet service.
 - a. Type ***99***1#**.
 - b. Click **Next**.
 - c. For CDMA and EV-DO modems, type **#777**.
 - d. Click **Next**.
10. On the Connection Availability screen, specify if anyone can use this connection or if the connection is just for your use. Select the desired radio button and click **Next**.

11. On the Internet Account Information screen, type the user name and the password for your account. In many cases, a user name and a password are not required, but some wireless providers require it. Check with your provider to see if they are needed.
Check the following two options to activate them:
 - Check the box if you want this account name and password to be used by everyone.
 - Check the box if you want this as your default Internet connection. Then click **Next**.
12. On the Completing the New Connection Wizard screen, your last task is to place a check in the box if you would like to add a shortcut to your desktop. Then click **Finish**.
13. A Connection screen displays on your desktop. Click **Properties** on the bottom of this screen.
14. The Properties window opens for you to make your connection.
Important: Make sure that Use dialing rules is not selected, and then click **OK**.
15. Once back at your Connection screen, click **Dial** at the bottom of the screen to start the connection.
16. The connection tells the modem to connect to your provider's Internet service. Once connected, you should see the connection status icon in your system tray at the bottom right-hand corner of your screen.

You can now open an Internet browser and access the Internet.

Disconnecting the Connection

1. To disconnect the connection, right click the connection icon in the system tray.
2. Scroll up and click **Disconnect**.

You are disconnected from the Internet.

Generic Dial-Up Method - Non-Windows

1. To disable the IP stack, enter **AT+WOPEN=0**
2. To set up an Access Point Name (APN):
AT+CGDCONT=1, "IP", "<APNSERVER>"
where <APNSERVER> is the APN server supplied by your carrier
3. Dial into the network using one of the following
 - If GPRS/EDGE/HSPA, use **ATD*99***1#**
 - If CDMA, EV-DO, use **ATD#777**

Setting the Serial Baud Rate

Your MultiModem iCell defaults to a serial baud rate of 115200 from the factory. For faster baud rates, you can manually set the modem to a higher speed (230400, 460800, or 921600) using the **AT+IPR=<baudspeed>**. However, you must make sure the host serial port is capable of the new speed. If the new speed is set and the host hardware is not capable of the higher speed, you will need to find a host that is capable or reset the nvram with the following:

Open a terminal application such as HyperTerminal with the following settings:

19200, 8, NONE, Hardware Flow Control

When the modem boots there is a 500ms window to do the following:

Issue: M
Response: MU
Issue: D
Response: M
Issue: S
Response: S<cr><if>OK<cr><lf>

Recovery

To do this manually, power off the modem, depress the **Caps Lock** key and hold down the **M** key. Power on the modem, a **MU** should display. Press the **D** key and then the **S** key quickly.

Appendix A – Regulatory Compliance



EMC, Safety, and R&TTE Directive Compliance

The CE mark is affixed to this product to confirm compliance with the following European Community Directives:

Council Directive 2004/108/EC of 31 December 2004 on the approximation of the laws of Member States relating to electromagnetic compatibility;

and

Council Directive 2006/95/EC of 12 December 2006 on the harmonization of the laws of Member States relating to electrical equipment designed for use within certain voltage limits;

and

Council Directive 1999/5/EC of 9 March 1999 on radio equipment and telecommunications terminal equipment and the mutual recognition of their conformity.

International Modem Restrictions

Some dialing and answering defaults and restrictions may vary for international modems. Changing settings may cause a modem to become non-compliant with national telecom requirements in specific countries. Also note that some software packages may have features or lack restrictions that may cause the modem to become non-compliant.

FCC Part 15 Class B Statement

This equipment has been tested and found to comply with the limits for a **Class B** digital device, pursuant to 47 CFR Part 15 regulations. The stated limits in this regulation are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy, and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Plug the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the 47 CFR rules. Operation of this device is subject to the following conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference that may cause undesired operation.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.


Industry Canada

This Class B digital apparatus meets all requirements of the Canadian Interference-Causing Equipment Regulations.

Cet appareil numérique de la classe B respecte toutes les exigences du Règlement Canadien sur le matériel brouilleur.

Appendix B – DC Power Cable

DC Power Cable Dimensions



Appendix C – Environmental Information

Waste Electrical and Electronic Equipment (WEEE) Statement

July, 2005

The WEEE directive places an obligation on EU-based manufacturers, distributors, retailers and importers to take-back electronics products at the end of their useful life. A sister Directive, ROHS (Restriction of Hazardous Substances) complements the WEEE Directive by banning the presence of specific hazardous substances in the products at the design phase. The WEEE Directive covers all Multi-Tech products imported into the EU as of August 13, 2005. EU-based manufacturers, distributors, retailers and importers are obliged to finance the costs of recovery from municipal collection points, reuse, and recycling of specified percentages per the WEEE requirements.

Instructions for Disposal of WEEE by Users in the European Union

The symbol shown below is on the product or on its packaging, which indicates that this product must not be disposed of with other waste. Instead, it is the user's responsibility to dispose of their waste equipment by handing it over to a designated collection point for the recycling of waste electrical and electronic equipment. The separate collection and recycling of your waste equipment at the time of disposal will help to conserve natural resources and ensure that it is recycled in a manner that protects human health and the environment. For more information about where you can drop off your waste equipment for recycling, please contact your local city office, your household waste disposal service or where you purchased the product.



REACH Statement

Registration of Substances:

After careful review of the legislation and specifically the definition of an "article" as defined in EC Regulation 1907/2006, Title II, Chapter 1, Article 7.1(a)(b), it is our current view Multi-Tech Systems, Inc. products would be considered as "articles". In light of the definition in § 7.1(b) which requires registration of an article only if it contains a regulated substance that "is intended to be released under normal or reasonable foreseeable conditions of use," our analysis is that Multi-Tech Systems, Inc. products constitute nonregisterable articles for their intended and anticipated use.

Substances of Very High Concern (SVHC)

Per the candidate list of Substances of Very high Concern (SVHC) published October 28, 2008 we have reviewed these substances and certify the Multi-Tech Systems, Inc. products are compliant per the EU "REACH" requirements of less than 0.1% (w/w) for each substance. If new SVHC candidates are published by the European Chemicals Agency, and relevant substances have been confirmed, that exceeds greater than 0.1% (w/w), Multi-Tech Systems, Inc. will provide updated compliance status.

Multi-Tech Systems, Inc. also declares it has been duly diligent in ensuring that the products supplied are compliant through a formalized process which includes collection and validation of materials declarations and selective materials analysis where appropriate. This data is controlled as a part of a formal quality system and will be made available upon request.

Restriction of the Use of Hazardous Substances (RoHS)



Multi-Tech Systems, Inc.

Certificate of Compliance

2002/95/EC

Multi-Tech Systems, Inc. confirms that this product now complies with the chemical concentration limitations set forth in the directive **2002/95/EC** of the European Parliament (Restriction Of the use of certain Hazardous Substances in electrical and electronic equipment - **RoHS**)

These Multi-Tech Systems, Inc. products do not contain the following banned chemicals:

Lead, [Pb] < 1000 PPM

Mercury, [Hg] < 1000 PPM

Hexavalent Chromium, [Cr+6] < 1000 PPM

Cadmium, [Cd] < 100 PPM

Polybrominated Biphenyl, [PBB] < 1000 PPM

Polybrominated Diphenyl Ether, [PBDE] < 1000 PPM

Notes:

1. Lead usage in some components is exempted by the following RoHS annex; therefore, higher lead concentration could be found.
 - a. Lead in high melting temperature type solders (i.e., tin-lead solder alloys containing more than 85% lead).
 - b. Lead in electronic ceramic parts (e.g., piezoelectronic devices).

C - RoHS

依照中国标准的有毒有害物质信息

根据中华人民共和国信息产业部 (MII) 制定的电子信息产品 (EIP)

标准 - 中华人民共和国《电子信息产品污染控制管理办法》(第 39 号), 也称作中国

RoHS, 下表列出了 Multi-Tech Systems Inc. 产品中可能含有的有毒物质 (TS) 或有害物质 (HS)

的名称及含量水平方面的信息。

成分名称	有害/有毒物质/元素					
	铅 (PB)	汞 (Hg)	镉 (CD)	六价铬 (CR6+)	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
印刷电路板	O	O	O	O	O	O
电阻器	X	O	O	O	O	O
电容器	X	O	O	O	O	O
铁氧体磁环	O	O	O	O	O	O
继电器/光学部件	O	O	O	O	O	O
IC	O	O	O	O	O	O
二极管/晶体管	O	O	O	O	O	O
振荡器和晶振	X	O	O	O	O	O
调节器	O	O	O	O	O	O
电压传感器	O	O	O	O	O	O
变压器	O	O	O	O	O	O
扬声器	O	O	O	O	O	O
连接器	O	O	O	O	O	O
LED	O	O	O	O	O	O
螺丝、螺母以及其它五金件	X	O	O	O	O	O
交流-直流电源	O	O	O	O	O	O
软件/文档 CD	O	O	O	O	O	O
手册和纸页	O	O	O	O	O	O
底盘	O	O	O	O	O	O

X 表示所有使用类似材料的设备中有害/有毒物质的含量水平高于 SJ/Txxx-2006 限量要求。

O 表示不含该物质或者该物质的含量水平在上述限量要求之内。

INDEX

C		M	
Canadian Regulations.....	31	Maintenance	8
CDMA technology	6		
CE Mark.....	31	P	
Circuit Switched Data	12	Panel Mounting	19
C-RoHS.....	35	Pin Functions	16
		Power Requirements.....	12
D		R	
DC Power Cable.....	32	REACH Statement.....	33
		RoHS Statement	34
E		S	
EMC, Safety, and R&TTE Directive Compliance	31	Signal LED	9
		Signal Strength	26
G		T	
GPS Specifications.....	15	Technical Specifications.....	12
GPS UL Statement	15	Temperatures	12
H		W	
Handling Precautions	8	WEEE Statement.....	33
I			
International Modem Restrictions	31		
L			
LED.....	9		